

dBm to Watts Conversion Chart

dBm	Watts	dBm	Watts	dBm	Watts
0	1.0 mW	16	40 mW	32	1.6 W
1	1.3 mW	17	50 mW	33	2.0 W
2	1.6 mW	18	63 mW	34	2.5 W
3	2.0 mW	19	79 mW	35	3 W
4	2.5 mW	20	100 mW	36	4 W
5	3.2 mW	21	126 mW	37	5 W
6	4 mW	22	158 mW	38	6 W
7	5 mW	23	200 mW	39	8 W
8	6 mW	24	250 mW	40	10 W
9	8 mW	25	316 mW	41	13 W
10	10 mW	26	398 mW	42	16 W
11	13 mW	27	500 mW	43	20 W
12	16 mW	28	630 mW	44	25 W
13	20 mW	29	800 mW	45	32 W
14	25 mW	30	1.0 W	46	40 W
15	32 mW	31	1.3 W	47	50 W

Power Measurement Units:

dBm - decibels relative to one milliwatt
dBW - decibels relative to one Watt

Gain Measurement Units:

dB_i - decibels relative to an isotrope
dB_d - decibels relative to a dipole



HyperLink Technologies, Inc.

1201 Clint Moore Road, Boca Raton, FL 33487 USA
 Tel: 561-995-2256 • Fax: 561-995-2432

[e-mail: sales@hyperlinktech.com](mailto:sales@hyperlinktech.com)
[Website: www.hyperlinktech.com](http://www.hyperlinktech.com)